

Delock RJ45 Port Doubler 1 RJ45 plug > 2 RJ45 jacks (1x Ethernet, 1x ISDN)

Description

This Y-adapter by Delock enables you to double a fixed installed network connection. Thus you can use one single cable for one 10/100 Ethernet and one ISDN connection. This application requires two adapters, which need to be connected with each cable side to the networking socket or patch panel. Hence you get two female ports instead of only one.



Specification

- Connectors: 1 RJ45 plug > 2 RJ45 jacks
- Anodized plastic case
- Pin layout:

Plug	1 2 3 6	4 5 7 8	
Socket1	1 2 3 6	-	Fast Ethernet
Socket2	-	4 5 3 6	ISDN
- Cable length 15cm

System requirements

- A 8 pin Cat.5 cable with RJ45 female ports on both sides (structured cabling, wall socket or patch panel)
- A second port doubler

Item No. 65441



EAN	4043619654413
Country of origin	China

Package content

- RJ45 Port Doubler

Package

- Poly bag

Images

